

incognito™

LR10 Learning Remote

For use with the Incognito Multi-Room System or Cambridge Audio Incognito compatible units

Editable source names

Clock and alarm features

Backlit display and keys

Hard-coded dedicated Incognito buttons

Learning buttons compatible with nearly all source equipment

High power IR output for extended transmission range

Local banks for control of bedroom TV etc

Macro facility and cloning feature

INTRODUCTION

Thank you for purchasing this Cambridge Audio Incognito LR10 Learning Remote Control. The LR10 is a flexible learning remote control designed to be used with our Incognito KP10 Keypad in three possible situations:

1. Where an Incognito KP10 Keypad is connected directly to a Cambridge Audio Incognito compatible Amplifier/Receiver.
2. Where an Incognito KP10 Keypad is connected to other manufacturers A-BUS Ready™ outputs.
3. As part of a full Incognito Multi-Room System using Incognito hubs.

The LR10 has eight device banks (SOURCE 1 etc.), plus two further Local banks which can be used to control sources local to the room in which the remote is being used. The eight device bank buttons have been pre-coded to send the correct Incognito codes to change sources on our hubs and Incognito compatible units, but these buttons can also be taught new codes as required.

There are six dedicated hard-coded buttons that control the features of the Incognito A-BUS Keypads: Standby, CCTV (only used when a Incognito VH10 Video Hub is installed), Select, Mute, Vol/Function Up and Vol/Function Down.


In addition there are 38 buttons per device bank that can be taught any IR code from the source equipment's own remote controls (e.g. a CD player remote). This allows the LR10 to control all functions of the source equipment in addition to controlling the Incognito system itself.

The eight device banks and all storage button names can be renamed so that any desired text can appear in the LCD display window.

A Macro function allows the LR10 to send out a chain of IR commands actioned by a single button-press. All 38 storage buttons and even the device bank buttons can contain a Macro of up to 20 steps.


A clock is provided which together with a Timer feature allows the LR10 to wake the user up to the SOURCE 1 input at any desired time.

UNIT DIAGRAM



- A** INFRARED TRANSMITTER AND LEARNING EYE
- B** DISPLAY (LCD) WINDOW
- C** DEVICE BUTTONS
- D** DEDICATED INCOGNITO MULTI-ROOM SYSTEM BUTTONS
- E** STORAGE BUTTONS
- F** LEARN/MACRO BUTTON
- G** EDIT BUTTON
- H** CLEAR BUTTON
- I** RESET BUTTON
- J** ALARM/TIMER ON/OFF

REAR OF LR10



INSTALLING BATTERIES

Use only Alkaline type batteries.


- (1) Remove the battery cover.
- (2) Insert 4 AAA/LR03/sum-4 batteries.
- (3) Close the battery cover until it clicks.

In case of battery replacement, all stored data is retained in non-volatile memory whilst the batteries are removed.


SETTING UP THE REMOTE CONTROL

REAL TIME CLOCK / DATE / MONTH / YEAR / WEEKDAY SETTING

1. On the back of the remote press EDIT once (using a paperclip or similar), to enter Real Time Clock mode. Display shows "CLOCK?" flashing. Press the ▲ or ▼ buttons to start editing.



2. Follow the steps below to set the desired values:



Keep holding ▲ or ▼ buttons to go through the 12/24 hour time format



For all settings pressing ▲ or ▼ scrolls through the desired values



Pressing ◀ or ▶ steps forwards or backwards through the Setting steps



Holding a cursor key will fast advance the function




3. When finished press the EDIT button or wait 15 seconds to exit Real Time Clock mode.


TIMER / ALARM

The LR10 has a timer function which allows the user to program a time to activate SOURCE 1 (e.g. to wake up to). When the programmed time is reached the remote automatically sends out the SOURCE 1 device code, a special wake-up code and any code programmed into the "1" button in the SOURCE 1 device bank. For instance, this allows the remote to activate an Incognito Keypad in that room, select SOURCE 1 and preset 1 (e.g. preferred radio station). The "1" button can also contain a Macro if desired (e.g. starting a CD player).

1. The remote needs to be positioned so that it has a clear line of sight to the Incognito Keypad.



2. On the back of the remote press EDIT twice (using a paperclip or similar), to enter Timer set mode. Display shows "TIMER?" flashing. Press the ▲ or ▼ buttons to start editing.



3. Follow the steps below to set the desired values:



Press ▲ or ▼ buttons to scroll through characters.



Press ▶ to move forward, ◀ to move back a character.



Days can be set to weekdays, weekends or every day of the week



4. Once the timer has been set a small alarm clock symbol appears on the display to indicate the timer is active.



5. When finished press the EDIT button or wait 15 seconds to exit Timer set mode.

Note: The Alarm On/Off button can be used at any time to turn on or off the timer/alarm without affecting the set time or days.


LEARN MODE

Note: Learning a new code will always overwrite the current data in a storage button including a Macro if one has been previously programmed.


1. On the back of the remote press the LEARN button once to enter Learn mode (using a paperclip or similar). Display shows "LEARN" flashing.




Place the original source remote (CD, DVD etc) facing the LR10, head to head, about 2-3 inches (5-8 cm) apart.



2. Press a device button (e.g. SOURCE 1) to select the device bank into which you wish to teach codes.



3. "LEARN" appears flashing on the display. Press the desired storage button (e.g. button 1). "LEARN" will stay static on the display.



4. On the original remote, press and hold the button whose IR code you want to teach into the LR10. Hold the button until the LR10 display reads "OK!".



When "OK!" appears, learning is complete and "LEARN" flashes again. Repeat steps 3-4 to learn another button. If no storage button is pressed after 8 seconds, the remote will automatically select the next storage button for you.

Note: When the remote is scanning for a code to be learnt it is not possible to exit Learn mode or select a different storage button. Wait 8 seconds until the remote times out and "LEARN" begins flashing again.

Continued on Page 8.

LEARN MODE cont.




If the display shows "ERROR", please ensure the correct steps are followed and repeat.



If the display shows "NO DATA", there was no signal from the original remote. Check the remotes are aligned, the original remote's batteries are good and repeat the process.

5. When finished press the LEARN button to exit Learn mode.




Note: It is NOT possible to teach new codes (or Macros) into the 6 dedicated Incognito System buttons, as they are always needed to control the Incognito Keypads.

A-BUS READY™ OUTPUTS ON OTHER MANUFACTURERS PRODUCTS

By default the Incognito LR10 device buttons have been pre-coded to send the correct Incognito codes to change sources on our hubs or Incognito compatible units. However these buttons can be taught new codes if required.


EXAMPLE: A-BUS Ready AV Receivers and Amplifiers from other manufacturers can also connect to Incognito A-BUS Keypads without an Incognito hub being required (Note: The KP10 Keypad should be in Standard A-BUS Mode). However, the LR10 will need to be programmed with the Receivers source/device codes as it is the Receiver that provides source selection in this scenario.



Continued on Page 8.

A-BUS READY™ OUTPUTS ON OTHER MANUFACTURERS PRODUCTS

- On the back of the remote press the LEARN button once to enter Learn mode (using a paperclip or similar). Display shows "LEARN" flashing.




- Press and hold for 5 seconds the device button (e.g. SOURCE 1) into which you want to teach the new code (and replace the pre-code). "LEARN" will stay static on the display.
- Press the appropriate source/device button on the AV Receiver remote, and hold until the display reads "OK!".

Note: Learning new codes into the source/device buttons replaces the Incognito codes that have been pre-coded into them.

To recover the original codes, perform a Clear Key or Clear Device on each device button in turn. This will reset its code to the dedicated Incognito source codes. Alternatively a Clear All operation will reset the whole remote to its default factory settings including all pre-codes. See the CLEARING STORED DATA section for more information.

BUTTON LABEL EDITING

When device or storage buttons are pressed, the display shows a default label. The LR10 however also allows users to change these labels (up to 8 characters). Please see AVAILABLE CHARACTER TABLE for the available character set.




- On the back of the remote press the EDIT button 3 times (using a paperclip or similar) to enter Label editing mode. "LABEL?" will appear on the display.
- Press the button whose display name you want to change.
- The display shows the name with the first character flashing. Press ▲ or ▼ buttons to scroll through characters. Press ► to move forward, ◀ to move back a character.
- Press the CLEAR button on the front of the remote to clear a character or insert a space. The name will be automatically centered when editing is complete.
- When finished press the EDIT button or wait 15 seconds to exit Edit mode.

SETTING A MACRO


A Macro is a chain of commands actioned by a single button press. Any storage button on the LR10 can contain a Macro of up to 20 steps. Delays of 1-99 seconds can be programmed between steps if desired.

EXAMPLE:

Creating a Macro called from the "O" button in the SOURCE 2 device page that turns on a CD player, waits 10 seconds, selects Track One and then Play.




Note: If a button is not pressed within approximately 15 seconds the LR10 will exit Macro mode.



Press and hold any Macro step to select a delay of 1-99 seconds before the next step is performed.

Continued on Page 12.

SETTING A MACRO cont.



- The display will show "STEP 2".

Press the "1" button

- The display will show "STEP 3".

Press the Play (▶) button.

- The display will show "STEP 4". On the back of the remote press the LEARN/MACRO button to finish, as no fourth step is required for this particular Macro.

The display will show "MAR.OK!" to confirm the Macro has been successfully learnt

OPERATING A MACRO

To call a Macro simply press the button that you taught the Macro into. The display will then show the steps and count down any delays programmed as the Macro is played back.

NOTES ON MACROS

Macros can be programmed into the source buttons in the same way as the storage buttons. In this case the first code sent out by the source button Macro will always be the source buttons own code, followed by the steps that you program in.

This first code will be the pre-coded Incognito source code or a new code if the source codes have been replaced with a learnt code as per the LEARNING CODES INTO DEVICE BUTTONS section.

A Macro cannot contain as a step a button that also contains a Macro. If you do program a Macro button as a step in another macro the LR10 will not do anything for this step, but all other steps will work as expected.


Delays of 1-99 seconds can be programmed between Macro steps, the default delay (if no delay is specified) is 0.5 seconds.

The dedicated Incognito Multi-Room System buttons CANNOT contain Macros.


CLONING

For ease of setup where a user may have more than one LR10, the complete contents of a remote (IR codes, Macros, button names and clock settings) can be transferred to another LR10 Remote by a "cloning" process. One remote must be set to transmit mode whilst the other set to receive mode, while joined by a cloning cable.

On the back of the remote press the EDIT button 4 times (using a paperclip or similar) on BOTH remotes to enter Clone mode. "REC/TRX" will appear on both the displays.



LR10 SET AS TRANSMITTER



LR10 SET AS RECEIVER

For the transmitting LR10, Press the ◀ button until "TRX" is flashing.



For the receiving LR10, Press the ◀ button until "REC" is flashing.



Press ENTER on the receiving remote. Display shows "WAITING".



Press ENTER on the transmitting remote. Display shows "SENDING".




The receiving remote display will now show "REC-ING" to indicate it is receiving data.

After approximately 7 minutes the displays should show "OK!" and return to normal operation. All data has been transferred. If the clone fails the receiver remote will show "ERROR" then "CL-REPT" (Clone Repeat). Put the transmitting remote back into Clone mode and repeat the process. A successful clone must be done to the receiving remote once the clone process has been started, as cloning overwrites the complete software in the receiving remote.

CLEARING STORED DATA

- To clear the IR code data in a single button, first select the device bank (SOURCE 1 etc) that contains that button then press the CLEAR button on the back of the remote once (using a paperclip or similar).



When the display shows "CLR KEY?" press the button to be cleared.

Note: Clearing a button does not affect the buttons name if it has been edited. Clearing a device button resets the code to the Incognito pre-code.

- To clear the IR code data in a whole device bank press the CLEAR button twice.



When the display shows "CLR DEV?" press the device button for the device bank (SOURCE 1 etc) to be cleared. All buttons in that device bank will be cleared.

Note: Clearing a device button does not affect the device name or any button names if they have been edited, but does clear all codes and Macros, and recovers the Incognito pre-code for the device bank button.

- To clear ALL the IR code data and Macros in the remote including all device, button and pre-code names and all button names, press the CLEAR button 3 times.



When the display shows "CLR ALL?" press and hold the ENTER button for approx 4 seconds.



The display will show "CLEARING", and may take a minute or so to complete.

- After each clearing operation (Clear Key, Clear Device or Clear All) the LR10 will automatically exit Clearing mode.

Note: When clearing, all source/device button codes will be returned to their factory default Incognito codes.

OPERATING THE REMOTE CONTROL

NORMAL OPERATION

- Press a device button.
- Press the desired storage button. If no IR code data is stored, the display shows EMPTY. If an IR code is present in the button the symbol will appear whilst the code is sent.

BUTTON AND DISPLAY BACKLIGHTING

Press the light button to turn on the remote's backlight function. All the buttons and the LCD display will light up for night time viewing.

LOW BATTERY INDICATOR

When the battery is low, a battery symbol appears on the display.



When the battery symbol starts flashing, all remote functions are locked until fresh batteries are installed.

RESET

Press the RESET button to restart the LR10. After reset, all data remains, but the real time clock and date have to be set again. Reset is used in the unlikely event that the LR10 locks up due to static discharge or other unforeseen events.

AVAILABLE CHARACTER TABLE



COMPLIANCE WITH FCC RULES:

THIS DEVICE COMPLIES WITH PART 15 OF THE FCC RULES. OPERATION IS SUBJECT TO THE FOLLOWING TWO CONDITIONS: (1) THIS DEVICE MAY NOT CAUSE HARMFUL INTERFERENCE, AND (2) THIS DEVICE MUST ACCEPT ANY INTERFERENCE RECEIVED, INCLUDING INTERFERENCE THAT MAY CAUSE UNDESIRABLE OPERATION.

Note: The manufacturer is not responsible for any radio or TV interference caused by unauthorised modifications to this equipment. Such modifications could void the user's authority to operate the equipment.



The Cambridge Audio Incognito LR10 Learning Remote Control complies with the Electromagnetic Compatibility (89/336/EEC) Directive when used according to this user guide.



A-BUS and A-BUS Ready are registered trademarks of LeisureTech Electronics Pty Ltd Australia



Cambridge Audio is a member of the Custom Electronic Design & Installation Association

AP16782/1



Incognito is a trademark of Cambridge Audio Ltd. All rights reserved.

www.cambridge-audio.com