

## Topaz SR10 Stereo Receiver



- True 85 Watts RMS per channel into 8 ohms
- Custom low flux toroidal transformer for audiophile performance
- Impressive connectivity with 4 rear inputs and 1 front mounted 3.5mm MP3 input
- Dedicated subwoofer output
- Fully switchable twin speaker outputs
- Remote control which also controls matching CD10 CD player
- Built-in MM phono stage
- 1/4" front mounted headphone socket
- Detachable IEC mains lead – fully upgradable
- Built in FM/AM tuner with RDS
- New casework design with a brushed aluminium front panel, rigid wrap-over lid assembly and carefully designed mechanicals for resonance control, all to improve sound quality and aesthetics.

## Detailed Specifications

<b>Power Output</b>	85 watts (into 8 ohms)
<b>Frequency response (-1dB)</b>	5Hz – 50kHz
<b>THD (unweighted)</b>	<0.01% @ 1kHz, 80% of rated power <0.15% 20Hz – 20kHz, 80% of rated power
<b>S/N ratio (ref 1W)</b>	>82dB (unweighted)
<b>Input Impedances</b>	47k ohms
<b>Power amp damping factor</b>	>50
<b>Max. Power consumption</b>	500W
<b>Bass/treble controls</b>	Shelving, ultimate boost/cut +/- 10dB @ 100Hz and 20kHz
<b>Bands (Europe)</b>	AM (522-1629kHz) FM (87.5-108MHz)
<b>Bands (US)</b>	AM (530-1710kHz) FM (87.5-108MHz)
<b>Aerial inputs</b>	FM 75 ohms, Coaxial AM 300 ohms wire loop/single wire.
<b>Dimensions (H x W x D)</b>	110 x 430 x 340mm (4.3 x 16.9 x 13.4")
<b>Weight</b>	8.1kg (17.8lbs)



# Topaz SR10 Stereo Receiver