

Topaz SR20 Stereo Receiver

November 2014



- True 100 Watts RMS per channel into 8 ohms
- Custom low flux toroidal transformer for audiophile performance
- Impressive connectivity with 3 rear analogue inputs, 3 digital inputs, 1 phono input and 1 front mounted MP3 input
- Dedicated subwoofer output
- Fully switchable twin speaker outputs
- Remote control which also controls matching CD10 CD player
- Built-in MM phono stage for turntable connection
- ¼" front mounted headphone socket
- Detachable IEC mains lead – fully upgradable
- Built-in FM/AM tuner with RDS
- Rigid casework design with a brushed aluminium front panel, wrap-over lid assembly and carefully designed mechanicals for resonance control, all to improve sound quality and aesthetics

Detailed Specifications

Power output	100 watts (into 8 ohms)
DAC	Wolfson WM8728
THD (unweighted)	<0.01% @ 1kHz, 80% of rated power <0.15% 20Hz – 20kHz, 80% of rated power
Frequency response (-1dB)	5Hz – 50kHz
S/N ratio (ref 1W)	>82dB (unweighted)
Input impedances	47k ohms
Power amp damping factor	>50
Maximum power consumption	500W
Bass/treble controls	Shelving, ultimate boost/cut, +/-10dB@100Hz and 20kHz
Subwoofer output	200Hz 2 nd order L+R, level follows volume setting
Digital inputs	PCM 16-24-bit S/P DIF coaxial 32-192kHz TOSlink optical 32-96kHz
Tuner	FM/AM (EU and US bands)
Dimensions (H x W x D)	110 x 430 x 340mm (4.3 x 16.9 x 13.4")
Weight	8.1kg (17.8lbs)



Topaz SR20 Stereo Receiver